

FUJIAN ZFLY POWER GENERATION CO.,LTD.

ADDRESS: ROOM 201, NO.2, JINYE ROAD, TIEHU VILLAGE, CHENGYANG TOWN, FUAN CITY, FUJIAN PROVINCE, CHINA

TECHNICAL SPECIFICATION OF Z SERIES RICARDO

Silent type Generator set	
Model	Z-R33/S
Prime power	24kw/30kva
Frequency	50HZ
Output voltage(adjustable)	230V/400V
Rated speed (r/min.)	1500
Dimension(L*W*H)	2000*930*1150 mm
Net weight	820kg

Technical parameters of Gen-Set:

Power factor	COSΦ=0.8
Phase/wires	3 phase 4 wires
Start mode	Electric
Controller	Digital MEBAY/SMARTGEN/DSE
Fuel consumption under 100% loading :	6.25 L/hour
Protection :	Low oil-pressure, High water temperature, Over-speed, Over-current.

Technical parameters of Engine:

Brand	RICARDO	Rated Power	24kw(30kva)
Model	ZH4100D	Standby Power	26kw(33kva)
Start mode	DC12/24V electric start	Original:	China
Cylinders	4	Cylinders Layout	Line
Speed-Governing	Mechanic	Displacement	3.61L
Aspirate way	Natural aspiration	Compression ratio	19:1
Inter-Cooling	water inter-cooling	Overload	110%
Fuel tank Capacity (L)	91	Lub Oil Capacity (L)	12

Technical parameters of Alternator:

Type :	Brushless	Frequency	50 Hz
Model :	ZFLY184G (copy stamford)	Prime power	25kw
Original	China	Rated voltage	230/400V
Protection class	IP23	Insulation class	H
Adjusting rate of stable voltage	±0.5 %	Adjusting range of voltage	±25 %
Constantworking type	S1	Voltage control	AVR

website: www.zflypower.com

Email: rok@zflypower.com

WhatsApp/wechat: 0086-13902297746

FUJIAN ZFLY POWER GENERATION CO.,LTD.

ADDRESS: ROOM 201, NO.2, JINYE ROAD, TIEHU VILLAGE, CHENGYANG TOWN, FUAN CITY, FUJIAN PROVINCE, CHINA



website: www.zflypower.com

Email: rok@zflypower.com

WhatsApp/wechat: 0086-13902297746